Baby Lock Venture
(Model BMVT10)
Software Update Version 1.50

October 2022

Introduction

If the software version of your Venture (Model BMVT10) is earlier than version 1.50, an update program is now available for download to improve its performance.

Version 1.50 update will provide the following changes:

1. Reset to Default menu is added to the settings screen.
    All saved data, customized settings and network information in the machine can be erased.
2. Improved the image quality of real-time camera view after canceling a scan.
3. Improved the functionality of detecting the embroidery positioning sticker on the fabric hooped in the versatile magnetic frame.

To confirm the software version of your BMVT10

1. Press the power switch to turn on your machine. The LCD screen comes on.

2. Touch anywhere on the initial screen, and then touch "OK".

3. Touch [settings icon] (Settings key) at the bottom of the display. The Settings screen appears.

4. Switch screens by using [<] and [>] to display the software version.

5. If the version shown on your machine is already Version 1.50 or later, it is not necessary to update your machine with the program on this page.

How to download the update program

1. Click the Details link on the web page for your machine. Click on the Manuals and Updates link, then select Download to download the Version 1.50 zipped update file.

2. Right-click on the downloaded zipped update file, select "Extract All", and follow the steps to extract the files. There will be two extracted files: these instructions and the actual update file (PR3_V150_TP.upf, size: 82,391KB).

How to update your machine's software

You must **format** a 4GB or 8GB USB flash drive to ensure that no data exists on the USB used to update your machine's software

---

* * * NOTE * * *

➢ **Do not turn off your machine while the machine is updating the software.**

If the machine's power is turned off while saving the software, it may result in damage to the machine.

---

1. Insert the USB Flash drive into the USB port on the computer.

2. Copy only the update file, PR3_V150_TP.upf to the USB Flash drive.

3. Safely remove the USB Flash drive from the USB port on the computer.

4. With the machine off, press the automatic threading button while turning the main power to on.

5. The following screen appears on the LCD. Touch the USB media key.

(The screen varies depending on the software version on your machine.)

6. Insert the USB Flash drive into the USB port on the machine.

7. Touch LOAD key.

Press LOAD after connecting the USB media containing the upgrade file.

Load

8. When the message "Upgrade complete" appears, the update file has been loaded.

9. Remove the USB Flash drive and turn the machine off and on again.

10. The machine's software has been updated to version 1.50.

Baby Lock Venture (Model BMVT10) Update History

➢ **Version 1.13 update will provide the following changes:**
1. Improved so that the selected needle bar stays at the current sewing position when the Home key is pressed.
2. Ensure proper detection of available Wi-Fi channels.

➢ **Version 1.11 update will provide the following changes:**
1. Versatile magnetic frame M / L can be recognized on the machine.
2. Update files can be downloaded directly to the machine by using wireless-LAN.
3. Data landing page can be selected when using the Link function.
4. Improved the function to be able to select and delete multiple pattern data at once.

NOTE: To learn more about new features, read the instructions about the update Ver.1.11 in the Operation Manual Addendum.

➢ **Version 1.03 update provided the following changes:**

1. Improved embroidery positioning sticker detection function.
2. Improved the position memory function in embroidering settings.

➢ **Version 1.02 update provided the following changes:**

1. Improved embroidery function when using stamp shape in IQ Designer.

➢ **Version 1.01 update provided the following changes:**

1. Revised built-in tutorial videos.
2. Improved search capability for embroidery positioning sticker with the built-in camera.
3. Improved editing character functionality.
4. Revised messages.
5. Improved embroidering quality when optional magnetic sash frame* is attached.
   * The accessory is sold separately.